



## P-Channel Enhancement Mode Field Effect Transistor




Top View



Bottom View

DFN3333-8L



### Product Summary

- $V_{DS}$  -60V
- $I_D$  -22.5A
- $R_{DS(on)}$  (at  $V_{GS}=-10V$ )  $<47\text{ m}\Omega$
- $R_{DS(on)}$  (at  $V_{GS}=-4.5V$ )  $<60\text{ m}\Omega$
- 100% EAS Tested

### General Description

- Split gate trench MOSFET technology
- Low  $R_{DS(on)}$  & FOM
- Low  $C_{rss}$
- Extremely low switching loss
- Excellent stability and uniformity
- Moisture Sensitivity Level 3
- Epoxy Meets UL 94 V-0 Flammability Rating
- Halogen Free

### Applications

- Power management
- Industrial DC/DC Conversion Circuits

### ■ Absolute Maximum Ratings ( $T_A=25^\circ\text{C}$ unless otherwise noted)

Parameter		Symbol	Limit	Unit
Drain-source Voltage		$V_{DS}$	-60	V
Gate-source Voltage		$V_{GS}$	$\pm 20$	V
Drain Current	Tc=25°C	$I_D$	-22.5	A
	Tc=100°C		-14.3	
Pulsed Drain Current <sup>A</sup>		$I_{DM}$	-90	A
Avalanche energy <sup>B</sup>		EAS	81	mJ
Total Power Dissipation <sup>C</sup>	Tc=25°C	$P_D$	43	W
	Tc=100°C		17.2	
Junction and Storage Temperature Range		$T_J, T_{STG}$	-55~+150	°C

### ■ Thermal resistance

Parameter		Symbol	Typ	Max	Units
Thermal Resistance Junction-to-Ambient <sup>D</sup>	$t \leq 10\text{s}$	$R_{\theta JA}$	20	25	°C/W
Thermal Resistance Junction-to-Ambient <sup>D</sup>	Steady-State		45	55	
Thermal Resistance Junction-to-Case	Steady-State		2.4	2.9	

### ■ Ordering Information (Example)

PREFERRED P/N	PACKING CODE	Marking	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
YJQ23GP06A	F1	Q23GP06A	5000	10000	100000	13" reel



# YJQ23GP06A

## ■ Electrical Characteristics ( $T_J=25^\circ\text{C}$ unless otherwise noted)

Parameter	Symbol	Conditions		Min	Typ	Max	Units
<b>Static Parameter</b>							
Drain-Source Breakdown Voltage	$\text{BV}_{\text{DSS}}$	$V_{\text{GS}}=0\text{V}, I_{\text{D}}=-250\mu\text{A}$		-60			V
Zero Gate Voltage Drain Current	$I_{\text{DSS}}$	$V_{\text{DS}}=-60\text{V}, V_{\text{GS}}=0\text{V}$	$T_J=25^\circ\text{C}$			-1	$\mu\text{A}$
			$T_J=55^\circ\text{C}$			-5	
Gate-Body Leakage Current	$I_{\text{GSS}}$	$V_{\text{GS}}= \pm 20\text{V}, V_{\text{DS}}=0\text{V}$				$\pm 100$	nA
Gate Threshold Voltage	$V_{\text{GS(th)}}$	$V_{\text{DS}}= V_{\text{GS}}, I_{\text{D}}=-250\mu\text{A}$		-1.3	-1.8	-2.5	V
Static Drain-Source On-Resistance	$R_{\text{DS(ON)}}$	$V_{\text{GS}}= -10\text{V}, I_{\text{D}}=-20\text{A}$			35	47	$\text{m}\Omega$
		$V_{\text{GS}}= -4.5\text{V}, I_{\text{D}}=-10\text{A}$			45	60	
Gate Resistance	$R_g$	$f=1\text{MHz}, \text{Open Drain}$			12		$\Omega$
Diode Forward Voltage	$V_{\text{SD}}$	$I_{\text{S}}=-20\text{A}, V_{\text{GS}}=0\text{V}$			-0.95	-1.3	V
Maximum Body-Diode Continuous Current	$I_{\text{S}}$					-23	A
<b>Dynamic Parameters</b>							
Input Capacitance	$C_{\text{iss}}$	$V_{\text{DS}}=-30\text{V}, V_{\text{GS}}=0\text{V}, f=1\text{MHz}$			1100		$\text{pF}$
Output Capacitance	$C_{\text{oss}}$				350		
Reverse Transfer Capacitance	$C_{\text{rss}}$				28		
<b>Switching Parameters</b>							
Total Gate Charge	$Q_g(-10\text{V})$	$V_{\text{GS}}=-10\text{V}, V_{\text{DS}}=-30\text{V}, I_{\text{D}}=-20\text{A}$			18.7		$\text{nC}$
Total Gate Charge	$Q_g(-4.5\text{V})$				8.8		
Gate-Source Charge	$Q_{\text{gs}}$				4.7		
Gate-Drain Charge	$Q_{\text{gd}}$				3.0		
Reverse Recovery Charge	$Q_{\text{rr}}$	$I_F=-20\text{A}, dI/dt=100\text{A}/\mu\text{s}$			8.2		$\text{ns}$
Reverse Recovery Time	$t_{\text{rr}}$				20.2		
Turn-on Delay Time	$t_{\text{D(on)}}$				7.5		
Turn-on Rise Time	$t_r$	$V_{\text{GS}}=-10\text{V}, V_{\text{DD}}=-30\text{V}, R_L=2.5\Omega, R_{\text{GEN}}=6\Omega$			39.5		$\text{ns}$
Turn-off Delay Time	$t_{\text{D(off)}}$				43.6		
Turn-off fall Time	$t_f$				55.1		

- A. Repetitive rating; pulse width limited by max. junction temperature.
- B.  $V_{\text{DD}}=50\text{V}, R_G=25\Omega, L=0.5\text{mH}, I_{\text{AS}}=18\text{A}$ .
- C.  $P_d$  is based on max. junction temperature, using junction-case thermal resistance.
- D. The value of  $R_{\text{BJA}}$  is measured with the device mounted on 1in2 FR-4 board with 2oz. Copper, in a still air environment with  $TA = 25^\circ\text{C}$ . The Power dissipation PDSM is based on  $R_{\text{BJA}} \leq 10\text{s}$  and the maximum allowed junction temperature of  $150^\circ\text{C}$ . The value in any given application depends on the user's specific board design.



## ■ Typical Performance Characteristics




Figure1. Output Characteristics




Figure2. Transfer Characteristics




Figure3. Capacitance Characteristics




Figure4. Gate Charge




Figure5. : On-Resistance vs. Gate to Source Voltage




Figure6. Normalized On-Resistance




Figure7. Normalized Gate Threshold Voltage




Figure8.Safe Operation Area






Figure9.Normalized Maximum Transient thermal impedance

**■ DFN3333-8L Package information**

Top View  
正面视图


Bottom View  
背面视图

Side View  
侧面视图

SYMBOL	MILLIMETER		
	MIN	NOM	MAX
D	3.15	3.25	3.35
E	3.15	3.25	3.35
A	0.70	0.80	0.90
A1	0.20	BSC	
A2			0.10
D1	2.20	2.35	2.50
E1	1.80	1.90	2.00
L1	0.35	0.45	0.55
L2	0.35	BSC	
b	0.20	0.30	0.40
e	0.65	BSC	

Note:

1. Controlling dimension: in millimeters.
2. General tolerance: +/-0.10mm.
3. The pad layout is for reference purposes only.



Suggested Solder Pad Layout  
Top View



## Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website <http://www.21yangjie.com>, or consult your nearest Yangjie's sales office for further assistance.