



Bridge Rectifiers

Features

- UL recognition, file #E230084
- Glass passivated chip junction
- Thin single in-line package
- High surge current capability
- Solder dip 275 °C max. 7 s, per JESD 22-B106

Typical Applications

General purpose use in AC/DC bridge full wave rectification for switching power supply, home appliances, office equipment, industrial automation applications.

Mechanical Data

- Package: JA
 - Molding compound meets UL 94 V-0 flammability rating, RoHS-compliant, Halogen free
- **Terminals**: Tin plated leads, solderable per J-STD-002 and JESD22-B102
- Polarity: As marked on body

■Maximum Ratings (Ta=25°C Unless otherwise specified)

PARAMETER		SYMBO	UNIT	D25JA05/	D25JA10A	D25JA20A	D25JA40A	D25JA60A	D25JA80A	D25JA100A		
Device marking code				D25JA05A	D25JA10A	D25JA20A	D25JA40A	D25JA60A	D25JA80A	D25JA100A		
Maximum Repetitive Peak Reverse Voltage		VRRM	V	50	100	200	400	600	800	1000		
Maximum RMS Voltage		VRMS	V	35	70	140	280	420	560	700		
Maximum DC blocking Vo	oltage	VDC	V	50	100	200	400	600	800	1000		
Average Rectified Output $T_c = 90^{\circ}C$				25.0								
Current @60Hz sine wave, R-load	Without heatsink Ta =25℃	IO	A				3.5					
Forward Surge Current (Non-repetitive) @60Hz Half-sine wave,1 cycle, Tj=25°C			A	360								
Forward Surge Current (Non-repetitive) @1ms, square wave, 1 cycle, Tj=25°C		IFSM		720								
Current squared time @1ms≤t≤8.3ms Tj=25°C,rating of per diode		l ² t	A ² S	537.8								
Storage temperature		Tstg	°C	-55 ~ +150								
Junction temperature		Tj	°C	-55 ~ +150								
Dielectric strength @ Terminals to case, AC 1 minute		Vdis	KV	2								
		Tor	kg∙cm	8								

1/4

■Electrical Characteristics (Ta=25°C Unless otherwise specified)

PARAMETER	SYMBOL	UNIT	TEST CONDITIONS	D25JA05A	D25JA10A	D25JA20A	D25JA40A	D25JA60A	D25JA80A	D25JA100A
Maximum instantaneous forward voltage drop per diode	VF	V	IFM=12.5A	1.0						
Maximum DC reverse current at rated DC	IR	μA	Тј =25°С	5						
blocking voltage per diode	••	μΑ	Tj =125℃	Tj=125℃ 100		100				
Typical junction capacitance	Cj	pF	Measured at 1MHz and Applied Reverse Voltage of 4.0 V.D.C	d Applied Reverse 116						

Thermal Characteristics $(T_a=25^{\circ}C \text{ Unless otherwise specified})$

PARAMETER		SYMBOL	UNIT	D25JA05A	D25JA10A	D25JA20A	D25JA40A	D25JA60A	D25JA80A	D25JA100A	
Thermal	Between junction and ambient, Without heatsink	RθJ-A	-		22.0						
Resistance	Between junction and case, With heatsink	R _{0J-C}	°C/W				1.0				

Note: Device mounted on 75mm x 45mm x 5.5mm Aluminum Plate Heatsink.

■Ordering Information (Example)

PREFERED P/N	PACKAGE CODE	UNIT WEIGHT(g)	MINIIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE	
D25JA05A ~ D25JA100A	B1	Approximate 4.3	15	750	1500	Tube	

Characteristics(Typical)





2/4







Outline Dimensions



JA						
Dim	Min	Max				
А	15.6	16.2				
В	28.7	29.3				
С	14.2	14.8				
D	1.5	1.7				
E	14.6	15.2				
F	7.3	7.7				
G	0.9	1.1				
Н	4.3	4.9				
I	3.3	3.9				
J	3.1	3.4				
К	8.7	9.3				
L	2.5	2.9				
М	0.4	0.6				
Ν	9.8	10.2				

3/4



Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with ordinary electronic equipment or devices, and not designed to be used with equipment or devices which require high level of reliability and the malfunction of with would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website http:// www.21yangjie.com , or consult your nearest Yangjie's sales office for further assistance.